

MARUSON, Regulador de voltage 800VA / 400W



Marca: Maruson

Código del producto: 1627, AVR-800

Disponibilidad: In Stock

Peso: 0.00kg

Dimensiones: 0.00cm x 0.00cm x 0.00cm

Short Description

- 800VA/400W AVR
- 4outlets (AVR+surge)
- Desk top and wall mountable design
- Resettable input overload protection circuit breaker
- Automatically regulates high and low voltage
- User-friendly visual indicators display

Descripción

Características:

MODEL

AVR-800

CAPACITY

800VA/400W

AC INPUT

Nominal Voltage

120/230VAC

Input Voltage Range

96~140VAC/176~278VAC

Phase

1 phase 2 wires

Frequency

50/60Hz (auto sensing)

AC OUTPUT

Nominal Voltage

120/230VAC

Phase

1 phase 2 wires

Frequency

50/60Hz

Outlets

4 outlets (4 AVR+surge)

PROTECTION

Surge Suppression	N/A
Tel/Fax/Network Surge	None
Suppression	None
Overload	Manual reset circuit switch
Over Current	Manual reset circuit switch
Short Circuit	Manual reset circuit switch

PHYSICAL

Dimension (W x H x D) (mm/in)	80 x 77 x 220 / 3.1 x 3.0 x 8.7
Net Weight (kg/lb)	1.2/2.6

Product specifications are subject to change without further notice. Battery backup time is based on a basic PC or half load and varies with equipment, configuration, battery age, temperature, ect.